ITRONIX®

TECHNICAL NOTE	Number	534
DATE: 14-Jul-00	Issue	2

TITLE:	Set-up of the Xircom Ethernet Adapter 10/100
ABSTRACT:	DIS5120-080-01

The below sequence has to be completed before the adapter will work correctly.

1) On power up complete the registration to start Windows 95.

2) After booting Windows 95. Right click on the 'My Computer' icon, click on the 'Properties' listing and the 'Device Manager' tab. Double click the 'Network Adapters' listing, double click the Xircom Credit Card Ethernet Adapter 10/100' listing.

3) Click the 'Resources' tab and remove the check mark from the 'Use Automatic Settings' box.

4) Locate the first memory range listing in the 'Resource Settings' box. Click on the words 'Memory Range' and click the 'Change Settings' button.

5) Using the up arrow to the right of the memory range listing change the memory range to 000D2000 - 000D2FFF.

6) Click OK. Windows 95 will read the changes and activate the new settings. The 'Link Integrity' LED should light up Green'.

The adapter should now be configured and ready for use.

The information contained in this document is copyright and may not be reproduced, stored in a retrieval system in any form by means of, electronic, mechanical, photocopying or otherwise without prior permission from the copyright holder, Itronix (UK) Limited.

Disclaimer. Whilst every precaution has been taken in the preparation of this document the publisher assumes no responsibility for errors and omissions. Neither is any liability assumed for damage resulting from the use of the information contained within this document.

Itronix (UK) Limited, Eden Road, Walsgrave Triangle Business Park, Coventry CV2 2TB, Telephone Coventry (024) 76 604040.